



GENIE

GENIE 11W WW E14 220-240V 1PF/6

Functional non-covered Energy saving lamp, with money saving high quality light and compact design. This lamp is small enough to fit neatly wherever you need extra bright light at home, enables easy replacement of most incandescent lamp all the way.

Product data


General Information		Starting Time (Nom)		0.3 s
Cap-Base	E14 [E14]	Warm Up Time To 60% Light (Min)	5 s	
Nominal Lifetime (Nom)	10000 h	Warm Up Time To 60% Light (Max)	40 s	
Switching Cycle	10000X	Power Factor (Nom)	0.6	
		Voltage (Nom)	220-240 V	
Light Technical		Controls and Dimming		
Color Code	827 [CCT of 2700K]	Dimmable	No	
Luminous Flux (Nom)	600 lm	Approval and Application		
Luminous Flux (Rated) (Nom)	600 lm	Energy Efficiency Label (EEL)	A	
Color Designation	Warm White (WW)	Mercury (Hg) Content (Max)	2 mg	
Lumen Maintenance 2000 h (Nom)	88 %	Mercury (Hg) Content (Nom)	1.5 mg	
Chromaticity Coordinate X (Nom)	463	Energy Consumption kWh/1000 h	11 kWh	
Chromaticity Coordinate Y (Nom)	420	Product Data		
Correlated Color Temperature (Nom)	2700 K	Full product code	871150080116610	
Luminous Efficacy (rated) (Nom)	55 lm/W	Order product name	GENIE 11W WW E14 220-240V 1PF/6	
Color Rendering Index (Nom)	80	EAN/UPC - Product	8711500801166	
LLMF At End Of Nominal Lifetime (Nom)	65 %	Order code	929689245301	
Operating and Electrical		Numerator - Quantity Per Pack	1	
Input Frequency	50 or 60 Hz	Numerator - Packs per outer box	6	
Power (Rated) (Nom)	11 W	Material Nr. (12NC)	929689245301	
Lamp Current (Nom)	80 mA			
Wattage Equivalent	50 W			

Net Weight (Piece)	0.080 kg
--------------------	----------

Warnings and Safety


- Breaking a lamp is extremely unlikely to have any impact on your health. If a lamp breaks, ventilate the room for 30 minutes and remove the parts, preferably with gloves. Put them in a closed plastic bag and take it to your local waste facilities for recycling. Do not use a vacuum cleaner.
- Compact fluorescent lamps have to be treated as special waste, they must be taken to your local waste facilities for recycling. The European Lighting Industry has set up an infrastructure, capable of recycling mercury, other metals, glass etc.

Dimensional drawing



Econ Genie ErP NG 11W/827 E14 220-240V

Product	D (max)	C (max)	F (max)
GENIE 11W WW E14 220-240V 1PF/6	35.0 mm	120 mm	44.5 mm



Econ Genie ErP NG 11W/827 E14 220-240V

Product	D (max)	C (max)	F (max)
GENIE 11W WW E14 220-240V 1PF/6	35.0 mm	120 mm	44.5 mm

