



GENIE

GENIE 14W WW E27 220-240V 1PF/6

Functional non-covered Energy saving lamp, with money saving high quality light and compact design. This lamp is small enough to fit neatly wherever you need extra bright light at home, enables easy replacement of most incandescent lamp all the way.

Product data


General Information		Starting Time (Nom)	
Cap-Base	E27 [E27]	Starting Time (Nom)	0.3 s
Nominal Lifetime (Nom)	10000 h	Warm Up Time To 60% Light (Min)	5 s
Switching Cycle	10000X	Warm Up Time To 60% Light (Max)	40 s
		Power Factor (Nom)	0.6
		Voltage (Nom)	220-240 V
Light Technical		Controls and Dimming	
Color Code	827 [CCT of 2700K]	Dimmable	No
Luminous Flux (Nom)	810 lm		
Luminous Flux (Rated) (Nom)	810 lm	Approval and Application	
Color Designation	Warm White (WW)	Energy Efficiency Label (EEL)	A
Lumen Maintenance 2000 h (Nom)	88 %	Mercury (Hg) Content (Max)	2 mg
Chromaticity Coordinate X (Nom)	463	Mercury (Hg) Content (Nom)	1.5 mg
Chromaticity Coordinate Y (Nom)	420	Energy Consumption kWh/1000 h	14 kWh
Correlated Color Temperature (Nom)	2700 K	Product Data	
Luminous Efficacy (rated) (Nom)	58 lm/W	Full product code	871150080120310
Color Rendering Index (Nom)	80	Order product name	GENIE 14W WW E27 220-240V 1PF/6
LLMF At End Of Nominal Lifetime (Nom)	65 %	EAN/UPC - Product	8711500801203
Operating and Electrical		Order code	929689243501
Input Frequency	50 or 60 Hz	Numerator - Quantity Per Pack	1
Power (Rated) (Nom)	14 W	Numerator - Packs per outer box	6
Lamp Current (Nom)	100 mA	Material Nr. (12NC)	929689243501
Wattage Equivalent	65 W		

Net Weight (Piece)	0.090 kg
--------------------	----------

Warnings and Safety


- Breaking a lamp is extremely unlikely to have any impact on your health. If a lamp breaks, ventilate the room for 30 minutes and remove the parts, preferably with gloves. Put them in a closed plastic bag and take it to your local waste facilities for recycling. Do not use a vacuum cleaner.
- Compact fluorescent lamps have to be treated as special waste, they must be taken to your local waste facilities for recycling. The European Lighting Industry has set up an infrastructure, capable of recycling mercury, other metals, glass etc.

Dimensional drawing



Econ Genie ErP NG 14W/827 E27 220-240V

Product	D (max)	C (max)	F (max)
GENIE 14W WW E27 220-240V 1PF/6	35.0 mm	127 mm	44.5 mm



Econ Genie ErP NG 14W/827 E27 220-240V

Product	D (max)	C (max)	F (max)
GENIE 14W WW E27 220-240V 1PF/6	35.0 mm	127 mm	44.5 mm

